

## BOOST-DVI-F-SC

DVI-D extender via Multi Mode fiber cable with SC,  
up to 1.2 km, 1080i, transmitter and receiver

### FEATURES

- Sender and receiver for the transfer of DVI signal up to 1.2 km via fiber optics
- SC Multi Mode fiber cable PC and monitor
- Also transmits audio signals to microphone and speaker
- REMAINING STOCK - limited quantity



## SPECIFICATIONS

|           |   |  |
|-----------|---|--|
| Afstand   | : | Fra nærmodul til fjernmodul Med 50/125 $\mu$ m fiberkabel op til 1,2 km Med 62,5/125 $\mu$ m fiberkabel op til 700 meter   |
| DVI       | : | DVI-D (digital DVI signal)   |
| Forsyning | : | 230 VAC til 12 VDC, 1,5 A netadaptere medfølger  |
| Lyd       | : | 2 x 3,5 mm jack hunstik til mikrofon og højttaler ind/udgang   |
| Opløsning | : | 1080i v/1,2 Km og 50/125 $\mu$ m fiberkabel 1080P v/800 meter og 50/125 $\mu$ m fiberkabel 1080i v/700 meter og 62,5/125 $\mu$ m fiberkabel 1080P v/350 meter og 62,5/125 $\mu$ m fiberkabel |



DANBIT A/S - Dansk Binær Teknik  
Værkstedvej 39 Køge , 4600 Danmark



+45 56 66 20  
20



salg@danbit.dk