

M485-COUNT-Q-I

3 Axis Encoder Module, Quadrant Count CW, CCW.
32 bits teller. 1 MHz. RS485. 10 - 30VDC.

FEATURES

- RS485 Modul med 3-Axpet Encoder Input
- 1MHz Frequency Input
- Input Spenning: Opptil 5VDC
- Andre spenninger er med ekstern motstand
- 32 biters teller
- Qvadrant, puls / dir, CW og CCW
- RS485 Port - 1200 - 115.2K Baud
- Spenning: 10 - 30VDC
- Mål: 123 x 72 x 35 mm



SPECIFICATIONS

Forsyning	:	10 - 30 VDC, 2 W via klemrække
Funktioner	:	Quadrant counting mode, CW/CCW counting mode, Pulse/Dir counting mode
Indgang	:	3 aksel encoder 32 bit
Isolation	:	Isoleret indgang (2500 VRMS): "0": 0 - 1 V , "1": 3,5 - 30 V Ikke-isoleret indgang med programmerbar tærskelværdi
Maks. hastighed	:	Frekvens maks. 1Mhz